



## TRASFORMATORI SERIE A 33



27x33



| COD       | PRIMARIO<br>V | POTENZA<br>VA | PIN     | SECONDARIO<br>V | PIN      | DISEGNO |
|-----------|---------------|---------------|---------|-----------------|----------|---------|
| A33029G/R | 24-48         | 2             | 4-2-1   | 24              | 10-8     | E/F     |
| A33030G/R | 115-230       | 3             | 1-3-5   | 12-12           | 6-7 9-10 | E/F     |
| A33031G/R | 120           | 3.3           | 1-5     | 2-14            | 6-7 9-10 | E/F     |
| A33032G/R | 115-115       | 2.5           | 1-2 4-5 | 9               | 6-10     | E/F     |
| A33033G/R | 240           | 3.3           | 1-5     | 16-2            | 9-10 6-7 | E/F     |
| A33034G/R | 415           | 3.3           | 1-5     | 16-2            | 9-10 6-7 | F       |
| A33035G/R | 440           | 3.3           | 1-5     | 16-2            | 9-10 6-7 | F       |
| A33036G/R | 480           | 3.3           | 1-5     | 2-14            | 6-7 9-10 | F       |
| A33037G/R | 415           | 2             | 1-5     | 21              | 7-9      | F       |
| A33038G/R | 380           | 2             | 1-5     | 12-12           | 6-7 9-10 | F       |
| A33039G/R | 230           | 2.2           | 1-2     | 7.5-24          | 4-5 6-7  | E/F     |
| A33040G/R | 400           | 2             | 1-5     | 14.5            | 7-9      | F       |
| A33041G/R | 400           | 1.5           | 1-5     | 18              | 7-9      | F       |
| A33042G/R | 325           | 1.5           | 1-5     | 32-32           | 6-7 9-10 | E/F     |



|            |        |      |      |        |
|------------|--------|------|------|--------|
| VERSIONE A | A=27   | B=33 | C=26 | D=6 mm |
| VERSIONE B | A=30,5 | B=35 | C=28 | D=6 mm |
| VERSIONE C | A=27   | B=33 | C=31 | D=6 mm |
| VERSIONE D | A=30,5 | B=35 | C=33 | D=6 mm |
| VERSIONE E | A=27   | B=33 | C=33 | D=6 mm |
| VERSIONE F | A=30,5 | B=35 | C=35 | D=6 mm |

vista lato pin