

TRASFORMATORI SERIE A 38 32x38



COD	PRIMARIO V	POTENZA VA	PIN	SECONDARIO V	PIN	DISEGNO
A38017G/R	230	3.8	1-6	17-9-15	7-8 9-10 1'	C/D
A38018G/R	18	3.6	1-5	6-6	6-7 9-10	C/D*
A38019G/R	24	3.6	1-5	9-9	6-7 9-10	C/D*
A38020G/R	115-115	3.6	1-3-5	9-9	6-7 9-10	C/D*
A38021G/R	115-115	4	1-3 4-6	9	12-10	C/D
A38022G/R	24-230	2	2-6	11	8-11	C/D
A38023G/R	230	3	1-6	7.5-7.5	12-9-7	C/D
A38024G/R	120	2.5	1-6	20	12-8	C/D
A38025R	575	2.5	1-6	20	12-8	D
A38026G/R	140	2.1	1-6	20	7-12	C/D
A38027G/R	240	2.1	1-6	20	7-12	C/D
A38028R	400	4	1-6	16	8-11	D
A38029R	415	2.5	1-6	20	12-8	D
A38030R	440	2.5	1-6	20	12-8	D
A38031G/R	230	2.5	1-6	12.5-12-5	12-10 9-8	C/D
A38032R	380	3.5	1-6	12-12	7-9 10-12	D
A38033R	400	3.5	1-6	15-15	7-9 10-12	D
A38034G/R	24-230	3	6-4-1	9	8-11	C/D
A38035G/R	250	3.3	2-6	17	7-11	C/D
A38036G/R	230	3.5	1-5	33-15	6-8 9-10	C/D*
A38037R	400	4	1-5	2-16	6-7 9-10	D*
A38038R	415	3.5	1-5	24-8	9-10 6-7	D*
A38039G/R	12-12	6	6-3 1-4	18-9	7-8 11-12	E/F
A38040G/R	24	4	1-6	26-5	11-12 7-8	E/F
A38041G/R	18	6	1-6	18-18	7-8 11-12	E/F
A38042G/R	24	5	1-5	8	7-11	E/F
A38043G/R	115	6	1-6	12	8-11	E/F
A38044G/R	127-240	4.5	6-3-1	15-22	7-8 11-12	E/F
A38045R	400	5	1-6	13	8-11	F
A38046R	230-380	6	6-3-1	12	9-10	F
A38047G/R	230	6	1-6	9-18	11-12 7-8	E/F
A38048G/R	230	6	1-6	11-18	11-12 7-8	E/F
A38049G/R	115-230	7	1-3-6	12	7-12	E/F
A38050G/R	230	7	1-6	8	11-12	E/F
A38051G/R	115-230	5	1-4-6	16	8-11	E/F
A38052G/R	230	5	1-6	13	8-11	E/F
A38053G/R	250	5	1-5	24	7-9	E/F*
A38054G/R	115-115	6	1-2 4-5	18-6.5	6-7 9-10	E/F*
A38055R	230-170	6	1-2 4-5	18-6.5	6-7 9-10	F*
A38056R	230-380	6	5-3-1	12	7-9	F*