

TRASFORMATORI SERIE A 30 25x30



COD	PRIMARIO V	POTENZA VA	PIN	SECONDARIO V	PIN	DISEGNO
A30018R	115	1.7	1-5	24	6-9	C
A30019R	230	1.7	1-5	24	6-9	C
A30A19R	380	1.7	1-5	24	6-9	C
A30B19R	24	1.5	1-5	12	7-10	C
A30C19R	48	1.5	1-5	12	7-10	C
A30D19R	127	1.5	1-5	12	7-10	C
A30E19R	240	1.5	1-5	12	7-10	C
A30F19R	415	1.5	1-5	12	7-10	C
A30G19R	230	1.5	1-5	6	7-9	C
A30020R	230	1.5	1-5	13.7	7-9	C
A30021R	230	1.6	1-5	13	7-9	C
A30022R	230	2	1-5	8.5	6-7	C
A30A22R	24	2.5	1-5	9	9-10	C
A30B22R	230	2	1-5	12-9	9-10 6-7	C
A30023R	115	1	2-5	11.8	10-8	C
A30024R	250	1	2-5	11.8	10-8	C
A30025R	230	2	1-5	12	9-10	C
A30026R	230	2	1-5	6	7-9	C
A30027R	230	2.4	1-5	12	7-9	C
A30A27R	100	2	1-5	15	7-9	C
A30B27R	230	1.5	1-5	18	7-9	C
A30C27R	230	1.8	1-5	18	7-9	C
A30D27R	230	2	1-5	28	7-9	C
A30028R	115-230	1.5	4-5-2	15	6-8	C
A30029R	115-230	1.5	4-5-3	18	9-10	C
A30030R	115-230	1.5	4-5-3	18-18-18	6-7-8 9-10	C
A30031R	115-230	1.5	4-2-5	20	6-8	C
A30032R	24-48	1.5	4-2-5	24	6-8	C
A30033R	230	2.3	1-5	9-9	6-7 9-10	C
A30034R	230	2	2-4	5-11	6-8 9-10	C
A30035R	230	1.5	1-5	18-18	6-7 9-10	C
A30036R	230	2	1-5	30-9	9-10 6-7	C
A30037R	12	2	1-5	10-10	6-7 9-10	C
A30038R	24	2	1-5	18-18	6-7 9-10	C
A30039R	24	2	1-5	18	7-9	C
A30040R	115-115	2	1-2 4-5	12-12	6-7 9-10	C
A30041R	380	2	1-5	12-12	6-7 9-10	C
A30042R	115-230	1.5	1-3-5	12	7-9	C
A30043R	450	0.9	1-5	26-10	6-7 9-10	C
A30044R	24	2.8	1-5	9-9	6-7 9-10	D
A30045R	42	3	1-5	8	7-9	D
A30046R	20-28	3	5-3-1	15	7-9	D