


TRASFORMATORI SERIE A 30 25x30



COD	PRIMARIO V	POTENZA VA	PIN	SECONDARIO V	PIN	DISEGNO
A30047R	24	2.2	1-2	7.5-24	4-5 6-7	D
A30048R	115-230	2	5-3-1	9	6-10	D
A30049R	24-115	2	1-2-4	20	10-8	D
A30050R	115-115	1.5	1-2 4-5	13.5-13.5	6-7 9-10	D
A30051R	230	2	1-5	17-17	6-8-10	D
A30052R	110	2.2	1-2	7.5-24	4-5 6-7	D
A30053R	24-110-230	2	1-2-3-5	24	8-10	D
A30054R	230	2.4	1-5	15	7-9	D
A30055R	230	2.8	1-5	15	7-9	D
A30056R	230	2	1-5	16	7-9	D
A30057R	230	2.3	1-5	18-18	6-7 9-10	D
A30058R	230	2.8	1-5	6	7-9	D
A30059R	230	2.8	1-5	9-9	6-7 9-10	D
A30060R	230	2.8	1-5	15-15	6-7 9-10	D
A30061R	230	3	1-5	8-15	9-10 6-7	D
A30062R	115-115	2.5	1-2 4-5	13	7-9	D
A30063R	230	2.8	1-5	10-18	2-4 7-9	D
A30064R	24-230	1.5	5-4-2	12-7	7-8 9-10	D



VERSIONE A	A=27	B=32	C=22	D=3 mm
VERSIONE B	A=27	B=32	C=24	D=3 mm
VERSIONE C	A=27	B=32	C=27	D=3 mm
VERSIONE D	A=27	B=32	C=29.5	D=3 mm

vista lato pin