

TRANSFORMER SERIES A 60**50x60**

CODE	PRIMARY V	POWER VA	PIN	SECONDARY V	PIN	DESIGN
A60033G/R	115-230	13	7-4-2	26	8-14	A/B
A60034G/R	230	14	1-7	14	9-13	A/B
A60035G/R	230	15	1-7	18-9	8-10 12-14	A/B
A60036G/R	230	18	1-7	24-10	8-9 13-14	A/B
A60037G/R	230	18	1-7	12-12	8-9 13-14	A/B
A60038G/R	115	15	2-6	14-14	9-10 12-13	A/B
A60039G/R	230	15	2-6	14-14	9-10 12-13	A/B
A60040G/R	220-240	15	7-6-5	22-22	11-12 13-14	A/B
A60041G/R	230	18	1-7	18-18	8-10 12-14	A/B
A60042G/R	230	15	1-7	36-9	8-10 12-14	A/B
A60043G/R	230-400	20	1-5-7	24	10-12	A/B
A60044G/R	380	10.5	2-6	9-18	8-10 12-14	A/B
A60045G/R	230	30	1-7	6-6	8-10 12-14	C/D
A60046G/R	230	30	1-7	9-9	8-9 13-14	C/D
A60047G/R	230	30	1-7	12-12	8-10 12-14	C/D
A60048G/R	230	30	3-7	19	12-14	C/D
A60049G/R	230	25	1-7	15	9-13	C/D
A60050G/R	230	30	1-7	11	9-13	C/D
A60051G/R	230	30	1-7	13	9-13	C/D
A60052G/R	115-115	30	7-5-1	26-8	8-10 12-14	C/D
A60053G/R	230-400	30	1-5-7	24	10-12	C/D
A60054G/R	115-230	24	7-4-1	46	8-14	C/D
A60055G/R	115-115	25	1-4 5-7	18-14	12-14 8-10	C/D
A60056G/R	115-230	24	7-4-1	18	8-14	C/D
A60057G/R	230	30	1-7	18-8	8-9 13-14	C/D
A60058G/R	230	30	1-7	18-12	8-9 13-14	C/D